



电话: 0755-84870203 邮箱: sales@highlightoptics.com

LLTF CONTRAST[™] THE ULTIMATE SUPERCONTINUUM FILTER UP TO 20W INPUT POWER



The Laser Line Tunable Filter (LLTF CONTRAST) is a non-dispersive tunable bandpass filter based on volume Bragg gratings. It combines very high optical density (> OD6), an outstanding out-of-band rejection, and wide tunability. The LLTF can be customized to cover the entire 400 nm to 2500 nm spectral range with a high spectral resolution. It can be coupled with a wide variety of broadband sources to create a tunable laser source. It can also be used as a cleanup filter for spectroscopy applications. There are numerous possible LLTF configurations whose spectral range and bandwidth can be finely tuned to fit specific needs. The specifications below of several tried-and-tested standard models may serve as a starting point.

TECHNICAL SPECIFICATIONS							
(extended and reduced spectral ranges also available**)	CONTRAST VIS CONTRAST SWIR CONTRAST EXT-IV		ST EXT-IV	CONTRAST X			
Spectral range	400-1000 nm	1000-2300 nm (2500 nm optional)	400-2300 nm (2500 nm optional)		X represents a custom spectral range		
Bandwidth (FWHM)***	< 2.5 nm	< 5.0 nm	400-1000 nm	1000-2300 nm	0.15 - 0.9 nm		
Out of band rejection	<-60dB@+40nm	<-60dB@+80nm	< 2.5 mm	< 5.0 mm	Depends on the bandwidth		
	<-30dB@±10nm	<-30dB@±20nm	<-30dB@±10nm	<-30dB@±20nm			
Maximum input average power	HP8 (up to 8W) HP20 (up to 20W)	HP8 (up to 8W) HP20 (up to 20W)	HP8 (up to 8W) HP20 (up to 20W)		HP4 (up to 4W)		
Peak efficiency	Typically 65%						
Optical density (OD)		Depends on spectral range					
Damage threshold	< 5 GW/cm² peak power @ 1064 nm, 8 ns						
Input beam diameter	< 5 mm						
Input beam divergence requirement (full angle)	< 1.5 mrad						
Wavelength resolution (relative)	FWHM / 8						
Pointing stability	< 1 mm total lateral displacement @ 1 m from filter						
Scanning speed (multiple step)	20 ms stabilization time for 0.01 nm step 20 ms stabilization time for 0.1 nm step 20 ms stabilization time for 0.2 nm step 25 ms stabilization time for 1 nm step 28 ms stabilization time for 2 nm step 35 ms stabilization time for 5 nm step 50 ms stabilization time for 10 nm step						
Software	PC (Windows10 - 64-bits) with PHySpec [™] control and analysis software (computer not included), connection via USB 2.0 (1.1 compatible)						
Dimensions (L x W x H)	9 x 6.3 x 6.7 (inches) 23 x 16 x 17 (cm)		11.8 x 9.1 x 6.7 (inches) 30 x 23 x 17.4 (cm)		9 x 6.3 x 6.7 (inches) 23 x 16 x 17 (cm)		
Operating temperature							
Storage temperature	0 to 50 °C						
Power requirement	Power requirement 120 VAC / 60 Hz 230 VAC / 50 Hz						
	**Eg: 500-2000 nm, 400-1700 nm, 500-900 nm, 400-650 nm, 650-1000 nm, 1000-1700 nm, 1700-2300 nm, etc.						
	***Valid if the divergence of the input beam does not exceed 1 mrad						



LLTF EXTENDED (500-2000 nm) OUTPUT POWER



Illustration of the out-of-band rejection of a volume holographic grating at λ c= 632 nm. Bands of ±45 nm are presented and an out-of-band rejection of -60 dB is obtained.



OPTIONS AND ACCESSORIES						
(extended and reduced spectral ranges also available**)	CONTRAST VIS	CONTRAST SWIR	CONTRAST EXT-IV	CONTRAST X		
Enhance SWIR	N/A	Up to 2500 nm				
Fibered output	A Ø_x-Ø_y rotation adjustment allows coupling optimization					
Harmonic filter	Blocks the harmonics coming from the region 400-500 nm	Blocks the harmonics coming from the regions 500-850 nm and/or 850- 1150 nm	Blocks the harmonics coming from the regions 400-500 nm and/or 500-850 nm and/or 850-1150 nm	The filter is chosen according to the spectral range		
Alignment kit (for free space)	In free space configuration (input/output), the alignment kit allows the user to rapidly find the correct alignment					
	**Eg: 500-2000 nm, 400-1700 nm, 500-900 nm, 400-650 nm, 650-1000 nm, 1000-1700 nm, 1700-2300 nm, etc.					

ACCESSORIES



FIBEROPTIC INPUT/OUTPUT

The LLTF Contrast, in its basic configuration, delivers a collimated free-space output beam. The fibered output option takes this beam and couples it into a fiber to fit the needs of various applications. An X-Y-Z translation adjustment allows coupling optimization. Compatible with most standard fiber connectors (ex. FC/PC, FC/APC, etc.)



ALIGNMENT KIT (FOR FREE-SPACE)

In free-space configuration, the alignment of the input laser into the LLTF is a challenging task without the proper tools. The alignment kit allows the user to rapidly find the correct alignment. Two irises, mounted on removable posts, are easily placed at the entrance of the filter. The laser beam then simply needs to follow the path created by the irises.

OPTIONS

HARMONIC FILTER

Like in every diffraction grating, the 2nd harmonic of a given wavelength is present in the output light of the LLTF Contrast[™]. Fortunately, we have a set of harmonic longpass filters that blocks this 2nd harmonic to bring it down to OD6. We generally recommend using these filters in order to get the full advantage of the LLTF optical purity. The harmonic filter performances we offer for the Contrast VIS and SWIR are described with the following graphics.

HARMONIC FILTER - VIS-HF2



HARMONIC FILTER - SWIR-HF2



HARMONIC FILTER - SWIR-HF12

